Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller

Data Sheet

Order Number: EC–QPNUB–TE

Revision/Update Information: This preliminary document supersedes the *DECchip 21142 Fast Ethernet LAN Controller Data Sheet* (EC–QPNUA–TE).

Digital Equipment Corporation
Maynard, Massachusetts

May 1996

While Digital believes the information included in this publication is correct as of the date of publication, it is subject to change without notice.

Digital Equipment Corporation makes no representations that the use of its products in the manner described in this publication will not infringe on existing or future patent rights, nor do the descriptions contained in this publication imply the granting of licenses to make, use, or sell equipment or software in accordance with the description.

© Digital Equipment Corporation 1996. All rights reserved.
Printed in U.S.A.

Digital, Digital Semiconductor, and the DIGITAL logo are trademarks of Digital Equipment Corporation.

Digital Semiconductor is a Digital Equipment Corporation business.

CardBus is a trademark of Personal Computer Memory Card International Association.
IEEE is a registered trademark of The Institute of Electrical and Electronics Engineers, Inc.
MicroWire is a registered trademark of BankAmerican Corporation.

All other trademarks and registered trademarks are the property of their respective owners.

Contents

1 Digital Semiconductor 21142 Overview 1
1.1 General Description 1
1.2 Features 2
1.3 Microarchitecture 4
2 Pinout 6
2.1 Signal Reference Tables 8
2.2 Pin Tables 20
2.3 Signal Grouping by Function 22
3 Electrical and Environmental Specifications 24
3.1 Voltage Limit Ratings 24
3.2 Temperature Limit Ratings 24
3.3 Supply Current and Power Dissipation 25
3.3.1 PCI I/O Voltage Specifications 25
3.3.2 PCI Reset 27
3.3.3 PCI Clock Specifications 28
3.3.4 Other PCI Signals 29
3.4 AUI and Twisted-Pair dc Specifications 30
3.5 Serial Interface Attachment Specifications 31
3.5.1 Serial Clock Timing 31
3.5.2 Internal SIA Mode AUI Timing—Transmit 32
3.5.3 Internal SIA Mode AUI Timing—Receive 33
3.5.4 Internal SIA Mode AUI Timing—Collision 33
3.5.5 Internal SIA Mode 10BASE-T Interface Timing—Transmit 35
3.5.6 Internal SIA Mode 10BASE-T Interface Timing—Receive 37
3.5.7 Internal SIA Mode 10BASE-T Interface Timing—Idle Link Pulse 38
3.6 MII Interface Specifications 39

3.7 MII Port Timing 39
3.7.1 MII 10/100Mb/s and 10Mb/s Timing—Transmit 39
3.7.2 MII 10/100Mb/s Timing—Receive 41
3.7.3 MII 10/100Mb/s Timing—Receive Error 43
3.7.4 MII 10/100Mb/s Timing—Carrier Sense and Collision 44
3.8 Boot ROM and Serial ROM Port Specification 45
3.9 Boot ROM Port Timing 45
3.9.1 Boot ROM Read Timing 45
3.9.2 Boot ROM Write Timing 47
3.10 Serial ROM Port Timing 48
3.11 External Register Timing 49
3.12 Joint Test Action Group—Test Access Port 51
3.12.1 JTAG dc Specifications 51
3.12.2 JTAG Boundary-Scan Timing 51
4 Mechanical Specifications 53

Figures

1 21142 Block Diagram 5
2 21142 Pinout Diagram (Top View) 7
3 PCI Reset Timing Diagram 27
4 PCI Clock Specifications Timing Diagram 28
5 Timing Diagram for Other PCI Signals 29
6 Serial Clock (XTAL) Timing Diagram 31
7 Internal SIA Mode AUI Timing Diagram—Transmit 32
8 Internal SIA Mode AUI Timing Diagram—Receive 33
9 Internal SIA Mode AUI Timing Diagram—Collision 33
10 Internal SIA Mode 10BASE-T Interface Timing Diagram—Transmit 35
11 Internal SIA Mode 10BASE-T Interface Timing Diagram—Receive 37
12 Internal SIA Mode 10BASE-T Interface Timing Diagram—Idle Link Pulse 38
13 MII Port Timing Diagram—Transmit 39
14 MII Port Timing Diagram—Receive 41
15 MII Port Timing Diagram—Receive Error 43
16 MII Port Timing Diagram—Carrier Sense and Collision 44
17 Boot ROM Read Timing Diagram 46
18 Boot ROM Write Timing Diagram 47

19 Serial ROM Port Timing Diagram 48
20 External Register Read Timing Diagram 49
21 External Register Write Timing Diagram 49
22 JTAG Boundary-Scan Timing Diagram 52
23 144-Pin PQFP Package 54
24 144-Pin TQFP Package 56

Tables

1 Index to Pinout Tables 6
2 Logic Signals 8
3 Power Pins 9
4 Functional Description of 21142 Signals 11
5 Input Pins 20
6 Output Pins 21
7 Input/Output Pins 21
8 Open Drain Pins 21
9 Signal Functions 22
10 Voltage Limit Ratings 24
11 Temperature Limit Ratings 24
12 Supply Current and Power Dissipation 25
13 I/O Voltage Specifications for 5.0-V Levels 25
14 I/O Voltage Specifications for 3.3-V Levels 26
15 PCI Reset Timing 27
16 PCI Clock Specifications 28
17 Other PCI Signals 29
18 AUI and Twisted-Pair dc Specifications 30
19 Serial Clock (XTAL) Timing Specifications 31
20 Internal SIA Mode AUI Timing Specifications—Transmit . . . 32
21 Internal SIA Mode AUI Timing Specifications—Receive and Collision 34
22 Internal SIA Mode 10BASE-T Interface Timing Specifications—Transmit 36
23 Internal SIA Mode 10BASE-T Interface Timing Specifications—Receive 37
24 Internal SIA Mode 10BASE-T Interface Timing Specifications—Idle Link Pulse 38
25 MII Interface 39

26 MII Port Timing—Transmit 40
27 MII Port Timing—Receive 42
28 MII Port Timing—Receive Error 43
29 MII Port Timing—Carrier Sense and Collision 44
30 Boot ROM and Serial ROM Port dc Specifications 45
31 Boot ROM Read Timing Specifications 46
32 Boot ROM Write Timing Specifications 47
33 Serial ROM Port Timing Characteristics 48
34 External Register Timing Specifications 50
35 JTAG dc Specifications 51
36 JTAG Interface Signal Timing Relationships 52
37 144-Pin PQFP Package Dimensions 55
38 144-Pin TQFP Package Dimensions 57

1 Digital Semiconductor 21142 Overview

The Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller (21142) supports the peripheral component interconnect (PCI) bus. It provides a direct interface connection to the PCI and adapts easily to most other standard buses. The 21142 software interface and data structures are optimized to minimize the host CPU load and to allow for maximum flexibility in the buffer descriptor management. The 21142 contains large onchip FIFOs, so no additional onboard memory is required. The 21142 provides an upgradable boot ROM interface and a CardBus interface connection.

1.1 General Description

The 21142 interfaces with the PCI bus by using onchip control and status registers (CSRs), and a shared CPU memory area that is set up mainly during initialization. This minimizes the processor involvement in the 21142 operation during normal reception and transmission. The 21142 is compliant with the *PCI Local Bus Specification, Revision 2.0 and Revision 2.1*. Bus traffic is also minimized by filtering out received runt frames and by automatically retransmitting collided frames without needing to repeat a fetch from shared memory.

On the network side, the 21142 provides three ports: a 10BASE-T 10Mb/s port, an attachment unit interface (AUI) 10Mb/s port, and a media-independent interface (MII) 100/10Mb/s port. The 10BASE-T port provides a direct Ethernet connection to the twisted-pair (TP) interface. The AUI port provides a direct Ethernet connection to the AUI. The MII port supports a full implementation of the MII standard. The 21142 is also capable of functioning in a full-duplex environment for the MII and 10BASE-T ports.

1.2 Features

The 21142 has the following features:

- Supports three network ports: 10BASE-T (10Mb/s), AUI (10Mb/s), and MII (10/100Mb/s)
- Provides standard 10/100Mb/s MII
- Contains an onchip integrated AUI port and a 10BASE-T transceiver
- Enables automatic detection and correction of 10BASE-T receive polarity
- Supports autodetection between 10BASE-T, AUI, and MII ports
- Supports full-duplex operation on both MII and 10BASE-T ports
- Provides internal and external loopback capability on all network ports
- Contains a variety of flexible address filtering modes
- Offers a unique, patented solution to Ethernet capture-effect problem
- Contains large independent receive and transmit FIFOs, with no additional onboard memory required
- Includes a powerful onchip direct memory access (DMA) with programmable burst size, providing for low CPU utilization
- Implements unique, patent-pending intelligent arbitration between DMA channels to minimize underflow or overflow
- Supports PCI clock speed frequency from dc to 33 MHz; network operation with PCI clock from 25 MHz to 33 MHz
- Supports an unlimited PCI burst
- Supports PCI read multiple command
- Supports early interrupt on transmit and receive to improve performance
- Implements low-power management with two power-saving modes (sleep or snooze)
- Supports both PCI 5.0-V and 3.3-V signaling environments
- Supports either big or little endian byte ordering for buffers and descriptors
- Contains a 4-bit, general-purpose programmable register and corresponding I/O pins
- Supports interrupts from two general-purpose pins
- Provides LED support for various network activity indications

- Provides MicroWire interface for serial ROM (1K and 4K EEPROM)
- Provides an upgradable boot ROM interface up to 256KB
- Supports automatic loading of subsystem vendor ID, subsystem ID, and CardBus card information structure (CIS) pointer from serial ROM to configuration registers
- Supports CardBus interface
- Implements JTAG-compatible test-access port with boundary-scan pins
- Supports IEEE 802.3 and ANSI 8802-3 Ethernet standards
- Implements low-power, 3.3-V complementary metal-oxide semiconductor (CMOS) technology

1.3 Microarchitecture

The following list describes the 21142 hardware components, and Figure 1 shows a block diagram of the 21142:

- PCI interface—Includes all interface functions to the PCI bus; handles all interconnect control signals; and executes PCI DMA and I/O transactions
- DMA—Contains dual receive and transmit controller; handles data transfers between CPU memory and onchip memory
- FIFOs—Contains two FIFOs for receive and transmit; supports automatic packet deletion on receive (runt packets or after a collision) and packet retransmission after a collision on transmit
- TxM—Handles all CSMA/CD[1] MAC[2] transmit operations, and transfers data from transmit FIFO to the ENDEC for transmission
- RxM—Handles all CSMA/CD receive operations, and transfers the data from the ENDEC to the receive FIFO
- SIA interface—Performs physical layer operations; implements the AUI and 10BASE-T functions, including the Manchester encoder and decoder functions
- General-purpose register—Enables software use for input or output functions and LED indications
- MII interface—Provides a full MII signal interface
- Serial ROM port—Provides a direct interface to the MicroWire ROM for storage of the Ethernet address and system parameters
- Boot ROM port—Provides an interface to perform read and write operations to the boot ROM; supports accesses to bytes or longwords (32-bit) and provides the ability to connect an external 8-bit register to the boot ROM port

[1] Carrier-sense multiple access with collision detection
[2] Media access control

Figure 1 21142 Block Diagram

2 Pinout

The 21142 is offered in two package styles: the 144-pin PQFP and the 144-pin TQFP. The tables in this section provide a description of the pins and their respective signal definitions.

Table 1 lists the tables in this section. Figure 2 shows the 21142 pinout for both the PQFP and the TQFP package types.

Table 1 Index to Pinout Tables

For this information . . .	Refer to . . .
Logic signals	Table 2
Power pins	Table 3
Functional signals description	Table 4
Input pins	Table 5
Output pins	Table 6
Input/output pins	Table 7
Open drain pins	Table 8
Signal functions	Table 9

Figure 2 21142 Pinout Diagram (Top View)

2.1 Signal Reference Tables

Table 2 provides an alphabetical list of the 21142 logic names and their pin numbers. Table 3 provides a list of the 21142 power pin numbers.

Table 2 Logic Signals

Signal	Pin Number	Signal	Pin Number	Signal	Pin Number
ad<0>	85	**ad<24>**	32	**br_ce_l**	87
ad<1>	84	**ad<25>**	31	**c_be_l<0>**	75
ad<2>	82	**ad<26>**	29	**c_be_l<1>**	60
ad<3>	81	**ad<27>**	28	**c_be_l<2>**	49
ad<4>	80	**ad<28>**	27	**c_be_l<3>**	33
ad<5>	78	**ad<29>**	25	**devsel_l**	55
ad<6>	77	**ad<30>**	24	**frame_l**	50
ad<7>	76	**ad<31>**	23	**gep<0>/aui_bnc**	100
ad<8>	70	**aui_cd–**	138	**gep<1>/activ**	101
ad<9>	69	**aui_cd+**	137	**gep<2>/rcv_match**	102
ad<10>	68	**aui_rd–**	140	**gep<3>/10bt_link**	103
ad<11>	66	**aui_rd+**	139	**gnt_l**	21
ad<12>	65	**aui_td–**	143	**idsel**	34
ad<13>	64	**aui_td+**	142	**int_l**	15
ad<14>	62	**br_a<0>**	88	**irdy_l**	51
ad<15>	61	**br_a<1>**	89	**iref**	108
ad<16>	48	**br_ad<0>**	90	**mii_clsn**	118
ad<17>	47	**br_ad<1>**	91	**mii_crs**	117
ad<18>	45	**br_ad<2>**	92	**mii_dv**	129
ad<19>	44	**br_ad<3>**	93	**mii_mdc**	134
ad<20>	43	**br_ad<4>**	96	**mii_mdio**	135
ad<21>	41	**br_ad<5>**	97	**mii_rclk**	128
ad<22>	40	**br_ad<6>**	98	**mii_rx_err**	127
ad<23>	39	**br_ad<7>**	99	**mii_rxd<0>**	130

(continued on next page)

Table 2 (Cont.) Logic Signals

Signal	Pin Number	Signal	Pin Number	Signal	Pin Number
mii_rxd<1>	131	**perr_l**	57	**tms**	12
mii_rxd<2>	132	**req_l**	22	**tp_rd–**	10
mii_rxd<3>	133	**rst_l**	16	**tp_rd+**	9
mii_tclk	124	**serr_l**	58	**tp_td–**	5
mii_txd<0>	122	**sr_ck**	114	**tp_td– –**	4
mii_txd<1>	121	**sr_cs**	115	**tp_td+**	6
mii_txd<2>	120	**sr_di**	113	**tp_td+ +**	7
mii_txd<3>	119	**sr_do**	112	**trdy_l**	52
mii_txen	123	**stop_l**	56	**vcap_h**	110
nc	86	**tck**	11	**xtal1**	106
par	59	**tdi**	13	**xtal2**	105
pci_clk	19	**tdo**	14	—	—

Table 3 Power Pins

Signal	Pin Number	Signal	Pin Number
vdd (3.3 V)	1, 2, 8, 18, 26, 36, 37, 46, 54, 67, 72, 73, 79, 95, 107, 125, 136, 141	**vss** (GND)	3, 17, 30, 35, 38, 42, 53, 63, 71, 74, 83, 94, 104, 116, 126, 144,
vddac (3.3 V)	109, 111		
vdd_clamp (5 V/3.3 V)	20		

Table 4 provides a functional description of each of the 21142 signals. These signals are listed alphabetically. The functional grouping of each pin is listed in Section 2.3.

The following terms describe the 21142 pinout:

- **Address phase**

  Address and appropriate bus commands are driven during this cycle.

- **Data phase**

  Data and the appropriate byte enable codes are driven during this cycle.

- **_l**

  All pin names with the _l suffix are asserted low.

The following pins in Table 4 have an internal pull-up:

sr_do
br_ce_l
tdi
tms

Pin **sr_cs** has an internal pull-down.

Table 4 uses the following abbreviations:

I = Input
O = Output
I/O = Input/output
O/D = Open drain
P = Power

Table 4 Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
ad<31:0>	I/O	See Figure 2.	32-bit PCI address and data lines. Address and data bits are multiplexed on the same pins. During the first clock cycle of a transaction, the address bits contain a physical address (32 bits). During subsequent clock cycles, these same lines contain 32 bits of data. A 21142 bus transaction consists of an address phase followed by one or more data phases. The 21142 supports both read and write bursts (in master operation only). Little and big endian byte ordering can be used.
aui_cd–	I	138	Attachment unit interface receive collision differential negative data.
aui_cd+	I	137	Attachment unit interface receive collision differential positive data.
aui_rd–	I	140	Attachment unit interface receive differential negative data.
aui_rd+	I	139	Attachment unit interface receive differential positive data.
aui_td–	O	143	Attachment unit interface transmit differential negative data.
aui_td+	O	142	Attachment unit interface transmit differential positive data.
br_a<0>	O	88	Boot ROM address line bit 0. In a 256KB configuration, this pin also carries in two consecutive address cycles, boot ROM address bits 16 and 17.
br_a<1>	O	89	Boot ROM address line bit 1. This pin also latches the boot ROM address and control lines by the two external latches.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
br_ad<7:0>	I/O	See Figure 2.	Boot ROM address and data multiplexed lines bits 7 through 0. In two consecutive address cycles, these lines contain the boot ROM address pins 7 through 2, **oe_l** and **we_l** in the first cycle; and these lines contain boot ROM address pins 15 through 8 in the second cycle. During the data cycle, bits 7 through 0 contain data.
br_ce_l	O	87	Boot ROM or external register chip enable.
c_be_l<3:0>	I/O	See Figure 2.	Bits 0 through 3 of the bus command and byte enable lines. Bus command and byte enable are multiplexed on the same PCI pins. During the address phase of the transaction, these 4 bits provide the bus command. During the data phase, these 4 bits provide the byte enable. The byte enable determines which byte lines carry valid data. For example, bit 0 applies to byte 0, and bit 3 applies to byte 3.
devsel_l	I/O	55	Device select is asserted by the target of the current bus access. When the 21142 is the initiator of the current bus access, it expects the target to assert **devsel_l** within 5 bus cycles, confirming the access. If the target does not assert **devsel_l** within the required bus cycles, the 21142 aborts the cycle. To meet the timing requirements, the 21142 asserts this signal in a medium speed (within 2 bus cycles).
frame_l	I/O	50	The **frame_l** signal is driven by the 21142 (bus master) to indicate the beginning and duration of an access. The **frame_l** signal asserts to indicate the beginning of a bus transaction. While **frame_l** is asserted, data transfers continue. The **frame_l** signal deasserts to indicate that the next data phase is the final data phase transaction.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
gep<0>/aui_bnc	I/O	100	This pin can be configured by software to be: • A general-purpose pin that performs either input or output functions. Can provide an interrupt when it is an input pin. • A control pin that provides an AUI (10BASE5) or BNC (10BASE2) select line. This pin is mainly used to enable the external BNC transceiver in 10BASE2 mode. When set, the 10BASE5 mode is selected. When reset, the 10BASE2 mode is selected.
gep<1>/activ	I/O	101	This pin can be configured by software to be: • A general-pupose pin that performs either input or output functions. Can provide an interrupt when it is an input pin. • A status pin that provides an LED that indicates either receive or transmit activity.
gep<2>/ rcv_match	I/O	102	This pin can be configured by software to be: • A general-purpose pin that performs either input or output functions. • A status pin that provides an LED that indicates a receive packet has passed address recognition.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
gep<3>/10bt_link	I/O	103	This pin can be configured by software to be: • A general-purpose pin that performs either input or output functions. • A status pin that provides an LED that indicates that the 10BASE-T link integrity test has completed successfully after the link was down.
gnt_l	I	21	Bus grant asserts to indicate to the 21142 that access to the bus is granted.
idsel	I	34	Initialization device select asserts to indicate that the host is issuing a configuration cycle to the 21142.
int_l	O/D	15	Interrupt request asserts when one of the appropriate bits of CSR5 sets and causes an interrupt, provided that the corresponding mask bit in CSR7 is not asserted. Interrupt request deasserts by writing a 1 into the appropriate CSR5 bit. If more than one interrupt bit is asserted in CSR5 and the host does not clear all input bits, the 21142 deasserts **int_l** for one cycle to support edge-triggered systems. This pin must be pulled up by an external resistor.
iref	I	108	Current reference input for the analog phase-locked loop logic.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
irdy_l	I/O	51	Initiator ready indicates the bus master's ability to complete the current data phase of the transaction. A data phase is completed on any rising edge of the clock when both **irdy_l** and target ready **trdy_l** are asserted. Wait cycles are inserted until both **irdy_l** and **trdy_l** are asserted together. When the 21142 is the bus master, **irdy_l** is asserted during write operations to indicate that valid data is present on the 32-bit **ad** lines. During read operations, the 21142 asserts **irdy_l** to indicate that it is ready to accept data.
mii_clsn	I	118	Collision detect is asserted when detected by an external physical layer protocol (PHY) device.
mii_crs	I	117	Carrier sense is asserted by the PHY when the media is active.
mii_dv	I	129	Data valid is asserted by an external PHY when receive data is present on the **mii_rxd** lines and is deasserted at the end of the packet. This signal should be synchronized with the **mii_rclk** signal.
mii_mdc	O	134	MII management data clock is sourced by the 21142 to the PHY devices as a timing reference for the transfer of information on the **mii_mdio** signal.
mii_mdio	I/O	135	MII management data input/output transfers control information and status between the PHY and the 21142.
mii_rclk	I	128	Supports either the 25-MHz or 2.5-MHz receive clock. This clock is recovered by the PHY.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
mii_rx_err	I	127	Receive error asserts when a data decoding error is detected by an external PHY device. This signal is synchronized to **mii_rclk** and can be asserted for a minimum of one receive clock. When asserted during a packet reception, it sets the cyclic redundancy check (CRC) error bit in the receive descriptor (RDES0).
mii_rxd<3:0>	I	See Figure 2.	Four parallel receive data lines. This data is driven by an external PHY that attached the media and should be synchronized with the **mii_rclk** signal.
mii_tclk	I	124	Supports the 25-MHz or 2.5-MHz transmit clock supplied by the external physical layer medium dependent (PMD) device. This clock should always be active.
mii_txd<3:0>	O	See Figure 2.	Four parallel transmit data lines. This data is synchronized to the assertion of the **mii_tclk** signal and is latched by the external PHY on the rising edge of the **mii_tclk** signal.
mii_txen	O	123	Transmit enable signals that the transmit is active in the MII port to an external PHY device.
nc	O	86	No connection.
par	I/O	59	Parity is calculated by the 21142 as an even parity bit for the 32-bit **ad** and 4-bit **c_be_l** lines. During address and data phases, parity is calculated on all the **ad** and **c_be_l** lines whether or not any of these lines carry meaningful information.
pci_clk	I	19	The clock provides the timing for the 21142 related PCI bus transactions. All the bus signals are sampled on the rising edge of **pci_clk**. The clock frequency range is between 25 MHz and 33 MHz.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
perr_l	I/O	57	Parity error asserts when a data parity error is detected. When the 21142 is the bus master and a parity error is detected, the 21142 asserts both CSR5 bit 13 (fatal bus error) and CFCS bit 24 (data parity report). Next, it completes the current data burst transaction, then stops operation. After the host clears the system error, the 21142 continues its operation. The 21142 asserts **perr_l** when a data parity error is detected in either a master-read or a slave-write operation. This pin must be pulled up by an external resistor.
req_l	O	22	Bus request is asserted by the 21142 to indicate to the bus arbiter that it wants to use the bus.
rst_l	I	16	Resets the 21142 to its initial state. This signal must be asserted for at least 10 active PCI clock cycles. When in the reset state, all PCI output pins are put into tristate and all PCI O/D signals are floated.
serr_l	O/D	58	If an address parity error is detected and CFCS bit 8 (**serr_l** enable) is enabled, 21142 asserts both **serr_l** (system error) and CFCS bit 30 (signal system error). When an address parity error is detected, system error asserts two clocks after the failing address. This pin must be pulled up by an external resistor.
sr_ck	O	114	Serial ROM clock signal.
sr_cs	O	115	Serial ROM chip-select signal.
sr_di	O	113	Serial ROM data-in signal.
sr_do	I	112	Serial ROM data-out signal.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
stop_l	I/O	56	Stop indicator indicates that the current target is requesting the bus master to stop the current transaction. The 21142 responds to the assertion of **stop_l** when it is the bus master, either to disconnect, retry, or abort.
tck	I	11	JTAG clock shifts state information and test data into and out of the 21142 during JTAG test operations. This pin should not be left unconnected.
tdi	I	13	JTAG data in is used to serially shift test data and instructions into the 21142 during JTAG test operations. This pin should not be left unconnected.
tdo	O	14	JTAG data out is used to serially shift test data and instructions out of the 21142 during JTAG test operations.
tms	I	12	JTAG test mode select controls the state operation of JTAG testing in the 21142. This pin should not be left unconnected.
tp_rd–	I	10	Twisted-pair negative differential receive data from the twisted-pair lines.
tp_rd+	I	9	Twisted-pair positive differential receive data from the twisted-pair lines.
tp_td– **tp_td– –**	O O	5 4	Twisted-pair negative differential transmit data. The positive and negative differential transmit data outputs are combined resistively outside the 21142 with equalization to compensate for intersymbol interference on the twisted-pair medium.
tp_td+ **tp_td+ +**	O O	6 7	Twisted-pair positive differential transmit data. The positive and negative differential transmit data outputs are combined resistively outside the 21142 with equalization to compensate for intersymbol interference on the twisted-pair medium.

(continued on next page)

Table 4 (Cont.) Functional Description of 21142 Signals

Signal	Type	Pin Number	Description
trdy_l	I/O	52	Target ready indicates the target agent's ability to complete the current data phase of the transaction. A data phase is completed on any clock when both **trdy_l** and **irdy_l** are asserted. Wait cycles are inserted until both **irdy_l** and **trdy_l** are asserted together. When the 21142 is the bus master, target ready is asserted by the bus slave on the read operation, which indicates that valid data is present on the **ad** lines. During a write cycle, it indicates that the target is prepared to accept data.
vcap_h	I	110	Capacitor input for analog phase-locked loop logic.
vdd	P	See Figure 2.	3.3-V supply input voltage.
vddac	P	109, 111	Supplies +3.3-V input for analog phase-locked loop logic.
vdd_clamp	P	20	Supplies +5-V or +3.3-V reference for clamp logic.
vss	P	See Figure 2.	Ground pins.
xtal1	I	106	Crystal input, or crystal oscillator input.
xtal2	O	105	Crystal feedback output pin used for crystal connections only. If this pin is unused, then it should be unconnected.

2.2 Pin Tables

This section contains four types of pin tables:

- Table 5 lists the input pins.
- Table 6 lists the output pins.
- Table 7 lists the input/output pins.
- Table 8 lists the open drain pins.

Table 5 Input Pins

Signal	Active Level	Signal	Active Level
aui_cd–	Low	**mii_rxd<3:0>**	—
aui_cd+	High	**mii_tclk**	—
aui_rd–	Low	**pci_clk**	—
aui_rd+	High	**rst_l**	Low
gnt_l	Low	**sr_do**	High
idsel	High	**tck**	—
iref	High	**tdi**	—
mii_clsn	High	**tms**	High
mii_crs	High	**tp_rd–**	Low
mii_dv	High	**tp_rd+**	High
mii_rclk	—	**vcap_h**	High
mii_rx_err	High	**xtal1**	—

Table 6 Output Pins

Signal	Active Level	Signal	Active Level
aui_td–	Low	**req_l**	Low
aui_td+	High	**sr_ck**	—
br_a<0>	High	**sr_cs**	High
br_a<1>	High	**sr_di**	High
br_ce_l	Low	**tdo**	High
mii_mdc	—	**tp_td–**	Low
mii_txd<3:0>	—	**tp_td– –**	Low
mii_txen	High	**tp_td+**	High
nc	—	**tp_td+ +**	High
		xtal2	High

Table 7 Input/Output Pins

Signal	Active Level	Signal	Active Level
ad<31:0>	—	**gep<3>/10bt_link**	—
br_ad<7:0>	—	**irdy_l**	Low
c_be_l<3:0>	Low	**mii_mdio**	—
devsel_l	Low	**par**	—
frame_l	Low	**perr_l**	Low
gep<0>/aui_bnc	—	**stop_l**	Low
gep<1>/activ	—	**trdy_l**	Low
gep<2>/rcv_match	—		

Table 8 Open Drain Pins

Signal	Active Level	Signal	Active Level
int_l	Low	**serr_l**	Low

2.3 Signal Grouping by Function

Table 9 lists the signals according to their interface function.

Table 9 Signal Functions

Interface	Function	Signal
PCI	Address and data	**ad<31:0>**, **par**
	Arbitration	**gnt_l**, **req_l**
	Bus command and byte enable	**c_be_l<3:0>**
	Device select	**devsel_l**, **idsel**
	Error reporting	**perr_l**, **serr_l**
	Interrupt	**int_l**
	System	**pci_clk**, **rst_l**
	Control signals	**frame_l**, **stop_l**, **irdy_l**, **trdy_l**
MII network port	Transmit data lines	**mii_txd<3:0>**
	Receive data lines	**mii_rxd<3:0>**
	Transmit, receive clocks	**mii_tclk**, **mii_rclk**
	Transmit enable	**mii_txen**
	Collision detect	**mii_clsn**
	Error reporting	**mii_rx_err**
	Data control	**mii_dv**, **mii_crs**
	MII management data clock	**mii_mdc**
	MII management data input/output	**mii_mdio**
Test access port	JTAG test operations	**tck**, **tdi**, **tdo**, **tms**
Serial ROM port	Serial ROM	**sr_ck**, **sr_cs**, **sr_di**, **sr_do**
Boot ROM port	ROM interface	**br_a<1:0>**, **br_ad<7:0>**, **br_ce_l**

(continued on next page)

Table 9 (Cont.) Signal Functions

Interface	Function	Signal
Power	3.3-V and 5.0-V supply input	**vdd**, **vddac**, **vdd_clamp**
	Ground	**vss**
General-purpose port and LEDs	General-purpose pins	**gep<3:0>**
	LED indicators	**activ**, **rcv_match**, **10bt_link**
	10BASE5/10BASE2 select	**aui_bnc**
Network connection	Analog phase-locked loop logic	**iref**, **vcap_h**
	AUI collision data	**aui_cd–**, **aui_cd+**
	AUI transmit and receive data	**aui_rd–**, **aui_rd+**, **aui_td–**, **aui_td+**
	Crystal oscillator	**xtal1**, **xtal2**
	Twisted-pair transmit and receive data	**tp_rd–**, **tp_rd+**, **tp_td–**, **tp_td– –**, **tp_td+**, **tp_td+ +**

3 Electrical and Environmental Specifications

This section contains the electrical and environmental specifications for the 21142.

Caution

Stresses greater than the maximum or less than the minimum ratings can cause permanent damage to the 21142. Exposure to the maximum or minimum ratings for extended periods of time lessen the reliability of the 21142.

3.1 Voltage Limit Ratings

Table 10 lists the voltage limit ratings.

Table 10 Voltage Limit Ratings

Parameter	Minimum	Maximum
Power supply voltage	+3.0 V	+3.6 V
vdd_clamp (5.0 V)	+4.75 V	+5.25 V
vdd_clamp (3.3 V)[1]	+3.0 V	+3.6 V
ESD protection voltage	—	2000 V

[1]In the 3.3 V signaling environment, **vdd_clamp** must not be greater than **vdd** + 0.3 V.

3.2 Temperature Limit Ratings

Table 11 lists the temperature limit ratings.

Table 11 Temperature Limit Ratings

Parameter	Minimum	Maximum
Storage temperature	–55°C	+125°C
Operating temperature	0°C	70°C

3.3 Supply Current and Power Dissipation

The values in Table 12 are estimates based on a PCI clock frequency of 33 MHz and a network data rate of 10/100Mb/s for MII.

Table 12 Supply Current and Power Dissipation

Mode	IDD[1] (mA)	Power[1] (mW)	IDD[2] (mA)	Power[2] (mW)
Normal	150	495	200[3]	720[3]
Snooze	85	280	140[3]	504[3]
Sleep	25	82	95[3]	342[3]
After power-up[4]	54	178	62	232

[1]Typical: 3.3 V @ 25°C

[2]Maximum: 3.6 V @ 25°C

[3]These values reflect worst case dynamic conditions.

[4]This value reflects a static condition.

3.3.1 PCI I/O Voltage Specifications

The 21142 meets the I/O voltage specifications listed in Table 13 and Table 14.

Table 13 I/O Voltage Specifications for 5.0-V Levels

Symbol	Parameter	Condition	Minimum	Maximum
V_{ih}	Input high voltage	—	2.0 V	**vdd_clamp** + 0.5 V
V_{il}	Input low voltage	—	–0.5 V	0.8 V
I_i[1]	Input leakage current	0.5 V <Vin<2.7 V	—	±70 µA
V_{oh}	Output high voltage	Iout=–2 mA	2.4 V	—
V_{ol}[2]	Output low voltage	Iout=3 mA, 6 mA	—	0.55 V
Cap[3]	Pin capacitance	—	5 pF	8 pF

[1]Input leakage currents include high-impedance output leakage for all bidirectional buffers with tristate outputs.

[2]Signals without pull-up resistors must have 3 mA low output current. Signals requiring pull-up resistors (including **frame_l, trdy_l, irdy_l, devsel_l, stop_l, serr_l,** and **perr_l**) must have 6 mA.

[3]Parameter design guarantee.

Table 14 I/O Voltage Specifications for 3.3-V Levels

Symbol	Parameter	Condition	Minimum	Maximum
V_{ih}	Input high voltage	—	0.475***vdd_clamp**	**vdd_clamp** + 0.5 V
V_{il}	Input low voltage	—	–0.5 V	0.325***vdd_clamp**
I_i[1]	Input leakage current	0.0 V <V_{in}<**vdd_clamp**	—	±70 µA
Voh	Output high voltage	Iout=–500 µA	0.9***vdd_clamp**	—
V_{ol}	Output low voltage	Iout=1500 µA	—	0.1***vdd_clamp**
Cap[2]	Pin capacitance	—	5 pF	8 pF

[1]Input leakage currents include high-impedance output leakage for all bidirectional buffers with tristate outputs.

[2]Parameter design guarantee.

3.3.2 PCI Reset

PCI reset (**pci_rst**) is an asynchronous signal that must be active for at least 10 active PCI clock (**pci_clk**) cycles. Figure 3 shows the PCI reset timing characteristics, and Table 15 lists the PCI reset signal limits.

Figure 3 PCI Reset Timing Diagram

LJ-03902.AI

Table 15 PCI Reset Timing

Symbol	Parameter	Minimum	Maximum	Condition
Trst	**pci_rst** pulse width	10*Tcycle	Not applicable	**pci_clk** active

3.3.3 PCI Clock Specifications

The clock frequency range[1] for the PCI is between 25 MHz and 33 MHz. Figure 4 shows the PCI clock specification timing characteristics and the required measurement points for both the 5.0-V and 3.3-V signaling environments. Table 16 lists the frequency-derived clock specifications.

Figure 4 PCI Clock Specifications Timing Diagram

Table 16 PCI Clock Specifications

Symbol	Parameter	Minimum	Maximum
Tcycle	Cycle time	30 ns	50 ns
Thigh[1]	**pci_clk** high time	11 ns	—
Tlow[1]	**pci_clk** low time	11 ns	—
Tr/Tf[2]	**pci_clk** slew rate	1 V/ns	4 V/ns

[1]Parameter design guarantee.

[2]Rise and fall times are specified in terms of the edge rate measured in V/ns. Parameter design guarantee.

[1] The PCI clock frequency is from dc to 33 MHz; network operational with the PCI clock from 25 MHz to 33 MHz.

3.3.4 Other PCI Signals

Figure 5 shows the timing diagram characteristics, and Table 17 lists the other PCI signals. This timing is identical to the timing for the general-purpose register signals.

Figure 5 Timing Diagram for Other PCI Signals

[1] Vtest is 1.5 V in 5.0-V signaling environment and is 0.4 * **vdd_clamp** in 3.3-V signaling environment.

LJ04719A.AI5

Table 17 Other PCI Signals

Symbol	Parameter	Minimum	Maximum
Tval[1]	clk-to-signal valid delay	2 ns	11 ns
Ton[2]	Float-to-active delay from clk	2 ns	—
Toff[2]	Active-to-float delay from clk	—	28 ns
Tsu	Input signal valid setup time before clk	7 ns	—
Th	Input signal hold time from clk	0 ns	—

[1]Load for this measurement is as specified in *PCI Local Bus Specification, Revision 2.0* and *PCI Local Bus Specification, Revision 2.1*.

[2]Parameter design guarantee.

3.4 AUI and Twisted-Pair dc Specifications

Table 18 lists the dc specifications for the AUI and twisted-pair parts of the SIA.

Table 18 AUI and Twisted-Pair dc Specifications

Symbol	Definition	Condition	Minimum	Maximum	Unit
AUI Pins					
V_{od}	Transmit differential output voltage (**aui_td**±)	78Ω termination	±550	±1200	mV
V_{odi}[1]	Transmit differential output idle voltage (**aui_td**±)	78Ω termination	–40	+40	mV
I_{odi}[1]	Transmit differential output idle current (**aui_td**±)	78Ω termination	–1	+1	mA
V_{asq+}[1]	Differential positive squelch threshold (**aui_rd±**)	—	175	275	mV
V_{asq-}[1]	Differential negative squelch threshold (**aui_rd±** and **aui_cd±**)	—	–275	–175	mV
V_{odu}[1]	Transmit differential output undershoot voltage on return to zero (**aui_td±**)	78Ω termination	—	–100	mV
Twisted-Pair Interface Pins					
V_{toh}	Output high voltage (**tp_td±** and **tp_td±±**)	I_{oh} = –25 mA	+ 2.5	V_{dd}	V
V_{tol}	Output low voltage (**tp_td**± and **tp_td±±**)	I_{ol} = 25 mA	V_{ss}	+ 0.5	V
V_{tsq+}[1]	Differential positive squelch threshold (**tp_rd±**)	—	300	520	mV
V_{tsq-}[1]	Differential negative squelch threshold (**tp_rd±**)	—	–520	–300	mV
V_{tdif}[1]	Differential input voltage range (**tp_rd**±)	—	–3.1	3.1	V

[1]Parameter design guarantee.

3.5 Serial Interface Attachment Specifications

This section describes the dc specifications and timing limits of the SIA unit.

3.5.1 Serial Clock Timing

Figure 6 shows the serial clock (TTL or CMOS) timing characteristics, and Table 19 lists the serial clock timing specifications.

Figure 6 Serial Clock (XTAL) Timing Diagram

LJ-04101.AI

Table 19 Serial Clock (XTAL) Timing Specifications

Symbol	Parameter	Minimum	Maximum
Tcr[1]	Rise time	—	4 ns
Tcf[1]	Fall time	—	4 ns
Tcycle	Cycle time	49.995 ns	50.005 ns
Tch[1]	Clock high time	0.4*Tcycle	0.6*Tcycle
Tcl[1]	Clock low time	0.4*Tcycle	0.6*Tcycle

[1]Parameter design guarantee.

3.5.2 Internal SIA Mode AUI Timing—Transmit

Figure 7 shows the internal SIA transmit timing characteristics for the AUI, and Table 20 lists the internal SIA transmit timing limits for the AUI.

Figure 7 Internal SIA Mode AUI Timing Diagram—Transmit

Table 20 Internal SIA Mode AUI Timing Specifications—Transmit

Symbol	Definition	Minimum	Maximum	Unit
Tatp[1]	**aui_td+, aui_td–** propagation delay from **xtal1** fall	—	30	ns
Tatr[1]	**aui_td+, aui_td–** rise time	2	8	ns
Tatf[1]	**aui_td+, aui_td–** fall time	2	8	ns
Tatm[1]	**aui_td+, aui_td–** rise and fall time mismatch (not shown)	—	1	ns
Tate	**aui_td±** end transmit delimiter length	345	405	ns

[1]Parameter design guarantee.

3.5.3 Internal SIA Mode AUI Timing—Receive

Figure 8 shows the internal SIA receive timing characteristics for the AUI, and Table 21 lists the internal SIA receive timing limits for the AUI.

Figure 8 Internal SIA Mode AUI Timing Diagram—Receive

3.5.4 Internal SIA Mode AUI Timing—Collision

Figure 9 shows the internal SIA collision timing characteristics for the AUI, and Table 21 lists the internal SIA collision timing limits for the AUI.

Figure 9 Internal SIA Mode AUI Timing Diagram—Collision

Table 21 Internal SIA Mode AUI Timing Specifications—Receive and Collision

Symbol	Definition	Minimum	Maximum	Unit
Tudo	**aui_rd±** start of frame pulse width	15	20	ns
Tudm	**aui_rd±** delay between opposite squelch crossings not recognized as end of packet	—	140	ns
Tudf	**aui_rd±** delay from last squelch crossing recognized as end of packet	150	—	ns
Tuco	**aui_cd±** start of collision pulse width	20	25	ns
Tucm	**aui_cd±** delay between squelch crossings not recognized as end of collision	—	140	ns
Tucf	**aui_cd±** delay from last squelch crossing recognized as end of collision	150	—	ns

3.5.5 Internal SIA Mode 10BASE-T Interface Timing—Transmit

Figure 10 shows the internal SIA transmit timing characteristics for the 10BASE-T interface, and Table 22 lists the internal SIA transmit limits.

Figure 10 Internal SIA Mode 10BASE-T Interface Timing Diagram—Transmit

Table 22 Internal SIA Mode 10BASE-T Interface Timing Specifications—Transmit

Symbol	Definition	Minimum	Maximum	Unit
Tpdp[1]	**tp_td+, tp_td–** propagation delay from **xtal1** fall	—	30	ns
Tpdr[1]	**tp_td+, tp_td++, tp_td–, tp_td– –** rise time	2	8	ns
Tpdf[1]	**tp_td+, tp_td++, tp_td–, tp_td– –** fall time	2	8	ns
Tpdm[1]	**tp_td+, tp_td++, tp_td–, tp_td– –** rise and fall time mismatch (not shown)	—	1	ns
Tpdc	**tp_td+** to **tp_td– –** and **tp_td–** to **tp_td++** delay	46	54	ns
Tped	**tp_td±** end transmit delimiter length	295	355	ns
Tpen	**tp_td++/– –** end transmit delimiter length	245	305	ns

[1]Parameter design guarantee.

3.5.6 Internal SIA Mode 10BASE-T Interface Timing—Receive

Figure 11 shows the internal SIA receive timing characteristics for the 10BASE-T interface, and Table 23 lists the internal SIA receive limits for the 10BASE-T interface.

Figure 11 Internal SIA Mode 10BASE-T Interface Timing Diagram—Receive

Table 23 Internal SIA Mode 10BASE-T Interface Timing Specifications—Receive

Symbol	Definition	Minimum	Maximum	Unit
Tsn	**tp_rd±** start of frame pulse width during smart squelch operation	15	20	ns
Tsf	**tp_rd±** maximum delay between opposite squelch crossings not to turn smart squelch off	140	150	ns
Tdm	**tp_rd±** delay between opposite squelch crossings not recognized as end of packet	—	140	ns
Tdf	**tp_rd±** delay from last squelch crossing recognized as end of packet	150	—	ns

3.5.7 Internal SIA Mode 10BASE-T Interface Timing—Idle Link Pulse

Figure 12 shows the internal SIA idle link pulse timing characteristics for the 10BASE-T interface, and Table 24 lists the internal SIA idle link pulse limits for the 10BASE-T interface.

Figure 12 Internal SIA Mode 10BASE-T Interface Timing Diagram—Idle Link Pulse

Table 24 Internal SIA Mode 10BASE-T Interface Timing Specifications—Idle Link Pulse

Symbol	Definition	Minimum	Maximum	Unit
Tpld	**tp_td**+ idle link pulse width	80	120	ns
Tplc	**tp_td++** and **tp_td– –** idle link pulse width	40	60	ns
Tplp	Idle link pulse period	8	24	ms

3.6 MII Interface Specifications

Table 25 lists the specifications for the MII interface.

Table 25 MII Interface

Symbol	Definition	Condition	Minimum	Maximum	Unit
V_{oh}	Output high voltage	I_{oh} = –4mA	2.4	—	V
V_{ol}	Output low voltage	I_{ol} = 4mA	—	0.4	V
V_{ih}	Input high voltage	—	2.0	—	V
V_{il}	Input low voltage	—	—	0.8	V
I_{in}	Input current	V_{in} = V_{cc} or **vss**	–10.0	10.0	µA
I_{oz}	Maximum tristate output leakage current	V_{in} = **vdd** or **vss**	–10.0	10.0	µA

3.7 MII Port Timing

This section describes the MII port timing limits.

3.7.1 MII 10/100Mb/s and 10Mb/s Timing—Transmit

Figure 13 shows the MII port transmit timing characteristics, and Table 26 lists the MII port transmit timing limits.

Figure 13 MII Port Timing Diagram—Transmit

Table 26 MII Port Timing—Transmit

Symbol	Definition	Minimum	Typical	Maximum	Unit
Tcc[1]	**mii_tclk** cycle time	—	40t[2]	—	ns
Tch[3]	**mii_tclk** high time	14t[2]	—	26t[2]	ns
Tcl[3]	**mii_tclk** low time	14t[2]	—	26t[2]	ns
Tcr	**mii_tclk** rise time	—	8	—	ns
Tcf	**mii_tclk** fall time	—	8	—	ns
Trv[4]	**mii_tclk** rise to **mii_txen** valid time or **mii_tclk** rise to **mii_txd** valid time	—	—	20	ns
Trh	**mii_txen** hold after **mii_tclk** rise time	5	—	—	ns

[1] ±50 parts per million.

[2] t=1 for 100Mb/s operation. t=10 for 10Mb/s operation.

[3] Parameter design guarantee.

[4] Outputs transmit data (**mii_txd**) and transmit enable (**mii_txen**) are driven internally from the rising edge of **mii_tclk**.

3.7.2 MII 10/100Mb/s Timing—Receive

Figure 14 shows the MII port receive timing characteristics, and Table 27 lists the MII port receive timing limits.

Figure 14 MII Port Timing Diagram—Receive

Table 27 MII Port Timing—Receive

Symbol	Definition	Minimum	Typical	Maximum	Unit
Tcc[1]	**mii_rclk** cycle time	—	40t[2]	—	ns
Tch	**mii_rclk** high time	10t[2]	—	26t[2]	ns
Tcl	**mii_rclk** low time	10t[2]	—	26t[2]	ns
Tcr	**mii_rclk** rise time	—	8	—	ns
Tcf	**mii_rclk** fall time	—	8	—	ns
Tts[3]	**mii_rxd** setup (both rise and fall transactions) to **mii_rclk** rise time or **mii_dv** setup (both rise and fall transactions) to **mii_rclk** rise time	10	—	—	ns
Tth[4]	**mii_rxd** hold (both rise and fall transactions) after **mii_rclk** rise time or **mii_dv** hold (both rise and fall transactions) after **mii_rclk** rise time	10	—	—	ns

[1] ±50 parts per million.

[2] t=1 for 100Mb/s operation. t=10 for 10Mb/s operation.

[3] Inputs receive data (**mii_rxd**) and data valid (**mii_dv**) are latched internally on the rising edge of **mii_rclk**. Parameter design guarantee.

[4] Parameter design guarantee.

3.7.3 MII 10/100Mb/s Timing—Receive Error

Figure 15 shows the MII port receive error timing characteristics, and Table 28 lists the MII port receive error timing limits.

Figure 15 MII Port Timing Diagram—Receive Error

Table 28 MII Port Timing—Receive Error

Symbol	Definition	Minimum	Maximum	Unit
Tts[1]	**mii_rx_err** setup (both rise and fall transactions) to **mii_rclk** rise time	10	—	ns
Tth[1]	**mii_rx_err** hold (both rise and fall transactions) after **mii_rclk** rise time	10	—	ns

[1]Input receive error (**mii_rx_err**) is latched internally on the rising edge of **mii_rclk**.

3.7.4 MII 10/100Mb/s Timing—Carrier Sense and Collision

Figure 16 shows the MII port carrier sense and collision timing characteristics, and Table 29 lists the MII port carrier sense and collision timing limits.

Figure 16 MII Port Timing Diagram—Carrier Sense and Collision

Table 29 MII Port Timing—Carrier Sense and Collision

Symbol	Definition	Minimum	Maximum	Unit
Tclh	**mii_crs**, **mii_clsn** high time	20	—	ns

3.8 Boot ROM and Serial ROM Port Specification

Table 30 lists the dc specifications for the boot ROM and serial ROM ports. These specifications apply in any mode in which the ports are used.

Table 30 Boot ROM and Serial ROM Port dc Specifications

Symbol	Definition	Condition	Minimum	Maximum	Unit
V_{oh}	Output high voltage	I_{oh} = –4 mA	2.4	—	V
V_{ol}	Output low voltage	I_{ol} = 4 mA	—	0.4	V
V_{ih}	Input high voltage	—	2.0	—	V
V_{il}	Input low voltage	—	—	0.8	V
I_{oz}[1]	Maximum tristate output leakage current	V_{out} = **vdd** or **vss**	–10	10	μA

[1]For **sr_do** and **br_ce_l** the maximum value is 1000.0 μA.

3.9 Boot ROM Port Timing

This section describes the boot ROM port timing.

3.9.1 Boot ROM Read Timing

Figure 17 shows the boot ROM read timing characteristics, and Table 31 lists the boot ROM read timing limits.

Figure 17 Boot ROM Read Timing Diagram

Table 31 Boot ROM Read Timing Specifications

Symbol	Parameter	Minimum	Maximum	Unit
Tavav	Read cycle time	240	—	ns
Tavqv	Address to output delay	—	240	ns
Telqv	**br_ce_l** to output delay	—	240	ns
Telqx[1]	**br_ce_l** to output low impedance	0	—	ns
Tehqz[1]	**br_ce_l** going high to output high impedance	—	55	ns
Toh[1]	Output hold from **br_ce_l** change	0	—	ns
Tads	Address setup to latch enable high	30	—	ns
Tadh	Address hold from latch enable high	30	—	ns

[1]Parameter design guarantee.

3.9.2 Boot ROM Write Timing

Figure 18 shows the boot ROM write timing characteristics, and Table 32 lists the boot ROM write timing limits.

Figure 18 Boot ROM Write Timing Diagram

Table 32 Boot ROM Write Timing Specifications

Symbol[1]	Parameter	Minimum	Unit
Tavav	Write cycle time	240	ns
Teleh[2]	**br_ce_l** pulse width	70	ns
Taveh[2]	Address setup to **br_ce_l** going high	50	ns
Tdveh[2]	Data setup to **br_ce_l** going high	50	ns
Tehdx[2]	Data hold from **br_ce_l** going high	10	ns
Tehax[2]	Address hold from **br_ce_l** high	15	ns
Tads	Address setup to latch enable high	30	ns
Tadh	Address hold from latch enable high	30	ns

[1]There are no maximum specifications.

[2]Parameter design guarantee.

3.10 Serial ROM Port Timing

Figure 19 shows the serial ROM port timing, and Table 33 lists the characteristics. This timing is identical to the timing for the MII management signals (**mii_mdio** and **mii_mdc**).

Figure 19 Serial ROM Port Timing Diagram

Table 33 Serial ROM Port Timing Characteristics

Symbol[1]	Definition	Maximum	Unit
Tsr[2]	Rise time	10	ns
Tsf[2]	Fall time	10	ns

[1]There are no minimum specifications.

[2]Parameter design guarantee.

3.11 External Register Timing

Figure 20 shows the external register read timing characteristics, and Figure 21 shows its write timing characteristics. Table 34 lists the external register timing specifications for both read and write operations.

Figure 20 External Register Read Timing Diagram

Figure 21 External Register Write Timing Diagram

Table 34 External Register Timing Specifications

Symbol	Parameter	Minimum	Maximum	Unit
Teleh	**br_ce_l** pulse width	120	—	ns
Read Timing				
Tpd	**br_ce_l** low to **br_ad<7:0>** valid high	—	20	ns
Tehqz[1]	**br_ce_l** high to **br_ad<7:0>** high impedance	—	20	ns
Write Timing				
Ts	Data setup time prior to **br_ce_l**	30	—	ns
Th	Data hold after **br_ce_l** high	30	—	ns

[1]Parameter design guarantee.

3.12 Joint Test Action Group—Test Access Port

This section provides the joint test action group (JTAG) test access port specifications.

3.12.1 JTAG dc Specifications

Table 35 lists the dc specifications for the JTAG pins.

Table 35 JTAG dc Specifications

Symbol	Definition	Condition	Minimum	Maximum	Unit
V_{oh}	Output high voltage	I_{oh} = –4 mA	2.4	—	V
V_{ol}	Output low voltage	I_{ol} = 4 mA	—	0.4	V
V_{ih}	Input high voltage	—	2.0	—	V
V_{il}	Input low voltage	—	—	0.8	V
I_{ip}	Input leakage current on pins with internal pullups (**tck**, **tdi**, and **tms**)	0.0 <Vin<**vdd**	—	+20/–1000[1]	μA
I_{oz}	Tristate output leakage current (**tdo**)	0.0 <Vout<**vdd**	—	±20	μA

[1] For **tck**, **tdi**, and **tms** pins that have internal pull-ups, the leakage current can get to 1.0 mA when Vin = 0 V.

3.12.2 JTAG Boundary-Scan Timing

Figure 22 shows the JTAG boundary-scan timing, and Table 36 lists the interface signal timing relationships.

Figure 22 JTAG Boundary-Scan Timing Diagram

Table 36 JTAG Interface Signal Timing Relationships

Symbol	Parameter	Minimum	Maximum	Unit
Tms_s	**tms** setup time	20	—	ns
Tms_h	**tms** hold time	5	—	ns
Tdi_s	**tdi** setup time	20	—	ns
Tdi_h	**tdi** hold time	5	—	ns
Tdo_d	**tdo** delay time	—	20	ns
Tck_r[1]	**tck** rise time	—	3	ns
Tck_f[1]	**tck** fall time	—	3	ns
Tck_cycle	**tck** cycle time	90	—	ns

[1]Parameter design guarantee.

4 Mechanical Specifications

The 21142 is contained in either a 144-pin PQFP package type or a 144-pin TQFP package type.

Figure 23 shows the mechanical layout of the PQFP and Table 37 lists PQFP package dimensions in millimeters.

Figure 24 shows the mechanical layout of the TQFP and Table 38 lists TQFP package dimensions in millimeters.

Figure 23 144-Pin PQFP Package

Table 37 144-Pin PQFP Package Dimensions

Symbol	Dimension	Value (mm)
LL	Lead length	1.60 reference[1]
e	Lead pitch	0.65 BSC[2]
L	Foot length	0.65 minimum to 1.03 maximum
A	Package overall height	4.07
A1	Package standoff height	0.25
A2	Package thickness	3.17 minimum to 3.67 maximum
b	Lead width	0.22 minimum to 0.38 maximum
c	Lead thickness	0.12 minimum to 0.23 maximum
ccc	Coplanarity	0.10
ddd	Lead skew	0.13
D	Package overall width	31.20 BSC[2]
D1	Package width	28.00 BSC[2]
E	Package overall length	31.20 BSC[2]
E1	Package length	28.00 BSC[2]
R	Ankle radius	0.13 minimum to 0.30 maximum

[1]The value for this measurement is for reference only.

[2]The default tolerances for basic (BSC) dimensions are:

0 mm to 5 mm	±0.1 mm
5 mm to 30 mm	±0.2 mm
30 mm to 100 mm	±0.3 mm

Figure 24 144-Pin TQFP Package

Table 38 144-Pin TQFP Package Dimensions

Symbol	Dimension	Value (mm)
LL	Lead length	1.00 reference[1]
e	Lead pitch	0.50 BSC[2]
L	Foot length	0.45 minimum to 0.75 maximum
A	Package overall height	1.60
A1	Package standoff height	0.05
A2	Package thickness	1.35 minimum to 1.45 maximum
b	Lead width	0.17 minimum to 0.27 maximum
c	Lead thickness	0.09 minimum to 0.20 maximum
ccc	Coplanarity	0.08
ddd	Lead skew	0.08
D	Package overall width	22.00 BSC[2]
D1	Package width	20.00 BSC[2]
E	Package overall length	22.00 BSC[2]
E1	Package length	20.00 BSC[2]
R	Ankle radius	0.08 minimum to 0.20 maximum

[1]The value for this measurement is for reference only.

[2]The default tolerances for basic (BSC) dimensions are:

0 mm to 5 mm	±0.1 mm
5 mm to 30 mm	±0.2 mm
30 mm to 100 mm	±0.3 mm

Technical Support and Ordering Information

Obtaining Technical Support

If you need technical support or help deciding which literature best meets your needs, call the Digital Semiconductor Information Line:

United States and Canada	**1–800–332–2717**
Outside North America	**+1–508–628–4760**

Ordering Digital Semiconductor Products

To order the Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller and for more information about an Evaluation Board kit, contact your local distributor.

The following table lists some of the semiconductor products available from Digital. To obtain a Digital Semiconductor Product Catalog, contact the Digital Semiconductor Information Line.

Product	Order Number
Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller (PQFP package)	21142—PA
Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller (TQFP package)	21142—TA
Digital Semiconductor 21140A PCI Fast Ethernet LAN Controller	21140—AC
Digital Semiconductor 21140A Evaluation Board Kit	21A40—TX
Digital Semiconductor 21041 PCI Ethernet LAN Controller	21041—AB
Digital Semiconductor 21041 Evaluation Board Kit	21A41—01

Ordering Digital Semiconductor Literature

The following table lists some of the available Digital Semiconductor literature. For a complete list, contact the Digital Semiconductor Information Line.

Title	Order Number
Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller Product Brief	EC–QPNTB–TE
Digital Semiconductor 21142 10/100Mb/s Ethernet LAN Controller Hardware Reference Manual	EC–QPNVA–TE
Digital Semiconductor 21140A PCI Fast Ethernet LAN Controller Product Brief	EC–QN7MB–TE
Digital Semiconductor 21140A PCI Fast Ethernet LAN Controller Data Sheet	EC–QN7PC–TE
Digital Semiconductor 21140A PCI Fast Ethernet LAN Controller Hardware Reference Manual	EC–QN7NC–TE
Digital Semiconductor 21041 PCI Ethernet LAN Controller Product Brief	EC–QAWVB–TE
Digital Semiconductor 21041 PCI Ethernet LAN Controller Data Sheet	EC–QAWWB–TE
Digital Semiconductor 21041 PCI Ethernet LAN Controller Hardware Reference Manual	EC–QAWXB–TE

Ordering Third-Party Literature

You can order the following third-party literature directly from the vendor:

Title	Vendor
PCI Local Bus Specification Revision 2.0 and Revision 2.1 PCI BIOS Specification Revision 2.0 and Revision 2.1	PCI Special Interest Group 1–800–433–5177 (U.S.) 1–503–797–4207 (International) 1–503–234–6762 (FAX)
Institute of Electrical and Electronics Engineers (IEEE) 802.3 and 1149.1	IEEE Service Center 1-800-701-4333 (U.S.) 1-908-981-0060 (International) 1-908-981-9667 (FAX)